

3-22-00

A

PATENT

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

ATTY DOCKET NO.: 8194-368

DATE: March 21, 2000

UTILITY PATENT APPLICATION TRANSMITTAL LETTER AND FEE TRANSMITTAL FORM (37 CFR 1.53(b))



BOX PATENT APPLICATION

Assistant Commissioner for Patents

Washington, DC 20231

Sir,

Transmitted herewith for filing under 37 CFR 1.53(b) is:

- ☒ a patent application
☐ a Continuation ☐ a Divisional ☐ a Continuation-in-Part (CIP)
 of prior application no.: ; filed .
☐ A Small Entity Statement(s) was filed in the prior application; Status still proper and desired.

Inventor(s) or Application Identifier:

Essam Sourour

Cary, North Carolina

Entitled: METHODS, SYSTEMS AND APPARATUS FOR PRECOMPENSATING FOR
INTERFERENCE AMONG TRANSMITTED CODED SIGNALS

Enclosed are:

1. ☒ Application Transmittal Letter and Fee Transmittal Form (*A duplicate is enclosed for fee processing*)
2. ☒ 27 pages of Specification (including 36 claims)
3. ☒ 10 sheets of Formal Drawings (35 USC 113)
4. ☒ Oath or Declaration
 - a. ☒ newly executed (*original or copy*)
 - b. ☐ copy from prior application (37 CFR 1.63(d) (*for continuation/divisional*) [Note Box 5 Below]
 - c. ☐ DELETION OF INVENTOR(S) (*Signed statement deleting inventor(s) named in the prior application*)
5. ☐ Incorporation By Reference (*useable if box 4b is checked*)
 The entire disclosure of the prior application, from which a copy of the oath or declaration is supplied under Box 4b, is considered as being part of the disclosure of the accompanying application and is hereby incorporated by reference therein.
6. ☐ Microfiche Computer Program (*Appendix*)
7. ☒ Assignment papers (*cover sheet(s) and document(s)*)
8. ☐ Small Entity Statement(s)
9. ☒ Information Disclosure Statement, PTO-1449, and 1 reference cited
10. ☐ Preliminary Amendment (*Please enter all claim amendments prior to calculating the filing fee.*)
11. ☐ English Translation Document
12. ☐ Certified Copy of


13. ☐ Sequence Listing/ Sequence Listing Diskette
 a. ☐ computer readable copy
 b. ☐ paper copy
 c. ☐ statement in support
 14. ☐ An Associate Power of Attorney
 15. ☒ Return Receipt Postcard (MPEP 503) *(Should be specifically itemized)*
 16. ☐ Other:

The fee has been calculated as shown below:

	Column 1 No. Filed	Column 2 No. Extra	Small Entity Rate Fee	Large Entity Rate Fee
BASIC FEE			\$345.00	\$690.00
TOTAL CLAIMS	36 - 20 =	16	x 09 = \$	x 18 = \$288.00
INDEP CLAIMS	5 - 3 =	2	x 39 = \$	x 78 = \$156.00
<input type="checkbox"/> MULTIPLE Dependent Claims Presented			+ 130 = \$	+ 260 = \$
<i>If the difference in Col. 1 is less than zero, Enter "0" in Col. 2</i>			Total \$	Total \$1134.00

- ☐ A check in the amount of \$ to cover the filing fee is enclosed.
- ☒ A check in the amount of \$1,174.00 is enclosed to cover the filing fee, PLUS the Assignment Recordation fee (\$40.00).
- ☒ The Commissioner is hereby authorized to charge payment of the following fees associated with this communication or credit any overpayment to Deposit Account No. 50-0220.
- ☒ Any additional filing fees required under 37 CFR 1.16.
- ☒ Any patent application processing fees under 37 CFR 1.17.

Respectfully submitted,



 Robert M. Meeks
 Registration No. 40,723

Correspondence Address:
 USPTO Customer Number: **20792**
 Myers Bigel Sibley & Sajovec, P.A.
 Post Office Box 37428
 Raleigh, North Carolina 27627
 Telephone (919) 854-1400
 Facsimile (919) 854-1401

CERTIFICATE OF EXPRESS MAILING

Express Mail Label No. EL533612477US
 Date of Deposit: March 21, 2000

I hereby certify that this correspondence is being deposited with the United States Postal Service "Express Mail Post Office to Addressee" service under 37 CFR 1.10 on the date indicated above and is addressed to Box Patent Application, Assistant Commissioner For Patents, Washington, DC 20231.


 Candi L. Riggs
 Date of Signature: March 21, 2000

METHODS, SYSTEMS AND APPARATUS FOR PRECOMPENSATING FOR INTERFERENCE AMONG TRANSMITTED CODED SIGNALS

BACKGROUND OF THE INVENTION

The present invention relates to communications systems and methods, and more particularly, to communications systems and methods in which signals are transmitted using codes.

5 Wireless communications systems are commonly employed to provide voice and data communications to subscribers. For example, analog cellular wireless communications systems, such as those designated AMPS (Advanced Mobile Phone System), NMT(Nordic Mobile Telephone)-450 and NMT-900, have long been deployed successfully throughout the world. Digital cellular wireless
10 communications systems such as those conforming to the North American standard IS-54 and the European standard GSM (Global Systems for Mobile Communications) have been in service since the early 1990's. More recently, a wide variety of wireless digital services broadly labeled as PCS (Personal Communications Services) have been introduced, including advanced digital cellular systems conforming to standards
15 such as TIA/EIA-136 and IS-95, lower-power systems such as DECT (Digital Enhanced Cordless Telephone) and data communications services such as CDPD (Cellular Digital Packet Data). These and other systems are described in *The Mobile Communications Handbook*, edited by Gibson and published by CRC Press (1996).

FIG. 1 illustrates a typical terrestrial cellular wireless communication system
20 **20**. The cellular wireless communications system **20** may include one or more terminals **22**, such as mobile terminals, radiotelephones or similar devices, communicating with a plurality of cells **24** served by base stations **26** and a mobile telephone switching office (MTSO) **28**. Although only three cells **24** are shown in FIG. 1, a typical cellular system may include hundreds of cells, may include more
25 than one MTSO, and may serve thousands of terminals.

The cells **24** generally serve as nodes in the communication system **20**, from which links are established between terminals **22** and the MTSO **28**, by way of the base stations **26** serving the cells **24**. Each cell **24** typically has allocated to it one or

more dedicated control channels and one or more traffic channels. A control channel is a dedicated channel used for transmitting cell identification and paging information. The traffic channels carry the voice and data information. Through the cellular system **20**, a duplex radio communication link may be effected between two mobile terminals **22** or between a mobile terminal **22** and a landline telephone user **32** through a public switched telephone network (PSTN) **34**. The function of the base station **26** is to handle radio communication between a cell **24** and mobile terminals **22**. In this capacity, the base station **26** functions as a relay station for data and voice signals.

As illustrated in FIG. 2, a satellite **42** may be employed to perform similar functions to those performed by a conventional terrestrial base station, for example, to serve areas in which population is sparsely distributed or which have rugged topography that tends to make conventional landline telephone or terrestrial cellular telephone infrastructure technically or economically impractical. A satellite wireless communications system **40** typically includes one or more satellites **42** (one shown) that serve as relays or transponders between one or more earth stations **44** (one shown) and terminals **23**, which may be mobile terminals, radiotelephones or the like. The satellite **42** conveys information over duplex links **46** to the terminals **23** and an earth station **44**. The earth station **44** may in turn be connected to a public switched telephone network **34**, allowing communications between terminals **23**, and communications between satellite terminals **23** and conventional terrestrial terminals or landline telephones. The satellite wireless communications system **40** may utilize a single antenna beam covering the entire area served by the system, or, as shown, the satellite may be designed such that it produces multiple minimally-overlapping beams **48**, each serving distinct geographical coverage areas **50** in the system's service region. The coverage areas **50** serve a similar function to the cells **24** of the terrestrial cellular system **20** of FIG. 1.

Several types of access techniques are conventionally used to provide wireless services to users of wireless systems such as those illustrated in Figs. 1 and 2.

Traditional analog cellular systems generally employ a system referred to as frequency division multiple access (FDMA) to create communications channels, while more modern digital wireless systems may use multiple access techniques such as time division multiple access (TDMA) and/or code division multiple access (CDMA) to provide increased spectral efficiency.

CDMA systems, such as those conforming to the widely known IS-95 standard, achieve increased channel capacity by using "spread spectrum" techniques wherein a channel is defined by modulating a data-modulated carrier signal by a unique channelization or spreading code (sequence), *i.e.*, a sequence that spreads an original data-modulated carrier over a wide portion of the frequency spectrum in which the communications system operates. Conventional spread-spectrum CDMA communications systems commonly use "direct sequence" (DS) spread spectrum modulation. In direct sequence modulation, a data-modulated carrier is directly modulated by a spreading code or sequence before being amplified by a power amplifier and transmitted over a communications medium, *e.g.*, an air interface. FIG. 3 illustrates a conventional DS transmitting technique, wherein symbol streams $d_1(t)$, $d_2(t)$, \dots , $d_K(t)$ are modulated according to respective spreading sequences (codes) $Q_1(t)$, $Q_2(t)$, \dots , $Q_K(t)$, producing spread-spectrum signals $r_1(t)$, $r_2(t)$, \dots , $r_3(t)$ that are summed to form a composite signal that is transmitted in a wireless communications medium.

CDMA systems currently in use typically use spreading codes selected from a set of orthogonal spreading codes. For example, according to IS-95, a base station serving a cell assigns forward link channelization codes to users from a set of 64 Walsh codes of length 64 chips. These codes are orthogonal when they are synchronous. Consequently, if there is little or no multipath in the propagation channel, the forward link channels from the same base station to all users in the cell generally remain orthogonal and users in the same cell cause little or no interference among one another.

Proposed CDMA systems may have to serve much larger numbers of users with much higher information rate demands than existing systems and, accordingly, may require many more channels (and channelization codes) than existing systems. For example, the proposed IS-2000 (cdma2000) standard is aimed at providing high data rate and multimedia applications. According to this standard, a user can simultaneously receive many data streams corresponding to many services such as voice, video, internet, fax, etc. To be able to provide all these data streams, the current proposed IS-2000 standard allows the cellular system to concurrently assign up to 3 codes, *i.e.*, 3 channels, to the same user.

Different approaches have been proposed to provide sufficient code choices for such systems. One approach involves allowing the use of orthogonal codes in

addition to the 64-bit Walsh codes used in current systems, for example, codes with lengths of 128, 256 and 512. This can significantly increase the number of available codes, even though the number of available codes may be constrained because simultaneous use of some codes of different lengths can destroy orthogonality.

- 5 A second approach involves the use of “quasi-orthogonal” codes, i.e., codes that exhibit low correlation between one another, but that are not completely orthogonal. A set of Walsh codes of length N includes N orthogonal codes. Letting W_i denote the i th Walsh code within a Walsh code set of length N chips, the cross-correlation among different Walsh codes of length N is given by:

$$10 \quad C_{i,j} = \int_0^T W_i(t) W_j(t) dt, \quad (1)$$

where $T = N$ is the period of Walsh code and τ is the chip duration. The cross-correlation $C_{i,j}$ for the Walsh code set meets the following constraint:

$$15 \quad C_{i,j} = \begin{cases} T & i = j \\ 0 & i \neq j \end{cases}. \quad (2)$$

Hence, different Walsh codes have zero cross-correlation and are orthogonal.

- Relaxing the cross-correlation constraint can increase the number of available codes. For example, a set of quasi-orthogonal codes consisting of 4 groups of N quasi-orthogonal codes can be formed, thus increasing the number of available codes to $4N$ codes. Denoting the i th codes in the n th group by Q_i^n , $i=1, 2, 3, \dots, N$ and $n=1, 2, 3$ and 4 , the quasi-orthogonal codes meet the following cross-correlation constraint:

$$25 \quad |C_{i,j}^{n,m}| = \left| \int_0^T Q_i^n(t) \tilde{Q}_j^m(t) dt \right| = \begin{cases} T & i = j \text{ and } m = n \\ 0 & i \neq j \text{ and } m = n \\ \leq xT_c & m \neq n \end{cases}, \quad (3)$$

- where $x \ll N$. Equation (3) indicates that the N codes within a group of the four groups are orthogonal ($i \neq j$ and $m = n$), while codes from different groups ($m \neq n$) have a low cross-correlation. Such a quasi-orthogonal coding scheme is described in TIA/EIA/IS-2000-2, Ballot Resolution Version (July, 1999).

As explained above, using quasi-orthogonal codes can increase the number of available codes, but codes from different groups are not orthogonal. Typically, a CDMA system utilizing such quasi-orthogonal codes would use all the codes in a first group and, once all of the codes of the first group are in use, start assigning codes from a second group. When a new code from the second group is used, the signal produced according to this code will generally exhibit interference arising from signals transmitted using the codes in the first group. However, the signals transmitted using the codes in the first group will generally exhibit a low level of interference as long as the number of codes in use from the second group is low. Under such conditions, channels that are assigned codes in the second group are disadvantaged in relation to channels defined by codes from the first group. To correct this imbalance, the system operator may select to make the number of activated codes from both groups equal. However, this can result in degradation of overall system performance. Accordingly, there is a need for techniques for transmitting coded signals which can improve system performance.

SUMMARY OF THE INVENTION

The present invention can meet this need by “precompensating” a transmitted signal based on knowledge of a signal that is to be concurrently transmitted therewith. According to embodiments of the present invention, compensation for interference in a second coded signal arising from a first, concurrently transmitted coded signal may be achieved by generating the second coded signal from an interference-compensated information symbol that is generated based on knowledge of the code and information symbol used to generate the first coded signal. For example, if the first and second coded signals are encoded according to respective codes selected from respective first and second orthogonal groups of a set of quasi-orthogonal codes, this compensation (or “pre-compensation”) can reduce interference in the second coded signal arising from lack of orthogonality of the codes from the first and second groups of codes. The amount of compensation can be adjusted to achieve a desired estimated signal quality, e.g., estimated signal to interference ratio, based on a scaling factor that can be determined based on the relative numbers of codes from each group of codes that are in use. In this manner, for example, signal-to-interference characteristics at a receiving station attempting to receive the second coded signal may be improved.

In particular, according to one embodiment of the present invention, an interference-compensated information symbol is generated from a source information symbol based on knowledge of an information symbol and a code used to generate a first coded signal. The first coded signal is then concurrently transmitted with a
5 second coded signal representing the interference-compensated information symbol encoded according to a second code.

According to one embodiment of the present invention, a first composite signal is generated from at least one information symbol according to at least one code from a first group of codes of a set of quasi-orthogonal codes. A first
10 interference-compensated information symbol is then generated from a first information symbol, the first composite signal and a code from a second group of codes of the set of quasi-orthogonal codes. A second coded signal representing the first interference-compensated information symbol encoded according to the code from the second group of codes is then transmitted concurrently with transmission of
15 the first coded signal. Preferably, the first interference-compensated information symbol is generated by integrating a product of the first composite signal and the complex conjugate of the code from the second group of codes over a symbol interval, scaling the integrated product by a scaling factor, and subtracting the scaled integrated product from the first information symbol to generate the first interference-
20 compensated information symbol. According to an aspect of the present invention, respective first and second numbers of codes from the first group of codes and the second group of codes to be used to transmit information symbols for the symbol interval are determined, and the scaling factor is determined based on the determined first and second numbers using, for example, a signal quality criterion, such as an
25 estimated signal to interference ratio (SIR) criterion.

According to another aspect of the present invention, mutual compensation is provided for signals generated according to codes from first and second groups of codes of a quasi-orthogonal set of codes. A second composite signal is generated from at least one information symbol according to at least one code from the second
30 group of codes. A second interference-compensated information symbol is then generated from a second information symbol, the second composite signal and a code from the first group of codes. A first coded signal representing the second interference-compensated information symbol encoded according to the code from the first group of codes and a second coded signal representing the first interference-

compensated information symbol encoded according to the code from the second group of codes are then concurrently transmitted.

According to another method aspect of the present invention, in a wireless communications system in which at least one base station is operative to transmit on
5 respective channels defined by respective spreading codes selected from a set of quasi-orthogonal spreading codes, the set of quasi-orthogonal spreading codes including a first group of orthogonal spreading codes and a second group of orthogonal spreading codes, an interference-compensated information symbol is generated from a source information symbol based on knowledge of an information
10 symbol and a code from the first group of codes used to generate a first coded signal. The first coded signal and a second coded signal representing the interference-compensated information symbol encoded according to a code from the second group of codes are concurrently transmitted.

According to yet another aspect of the present invention, a communications
15 system includes at least one transmitter that generates an interference-compensated information symbol from a source information symbol based on knowledge of an information symbol and a code used to generate a first coded signal. Then at least one transmitter concurrently transmits the first coded signal and a second coded signal representing the interference-compensated information symbol encoded according to
20 a second code. According to one embodiment of the present invention, the at least one transmitter may include a composite signal generating circuit that generates a composite signal from at least one first information symbol according to a corresponding at least one code from a first group of codes of a set of quasi-orthogonal codes. An interference-compensating coded signal generating circuit
25 generates the interference-compensated information symbol from the source information symbol, the composite signal and a code from a second group of codes of the set of quasi-orthogonal codes, and generates the second coded signal from the interference-compensated information symbol according to the code from the second group of codes.

30 According to another aspect of the present invention, a wireless communications base station includes an interference-compensating transmitter operative to transmit on respective channels defined by respective spreading codes selected from a set of quasi-orthogonal spreading codes, the set of quasi-orthogonal spreading codes including a first group of orthogonal spreading codes and a second

group of orthogonal spreading codes. The transmitter is further operative to generate an interference-compensated information symbol from a source information symbol based on knowledge of an information symbol and a code from the first group of codes used to generate a first coded signal and to concurrently transmit a second coded signal representing the interference-compensated information symbol encoded according to a code from the second group of codes. The transmitter may include a composite signal generating circuit that encodes at least one information symbol according to at least one code from the first group of codes to generate a composite signal, and an interference-compensating coded signal generating circuit that integrates a product of the composite signal and the complex conjugate of the code from the second group of codes over a symbol interval, scales the integrated product by a scaling factor, and subtracts the scaled integrated product from the source information symbol to generate the interference-compensated information symbol.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic diagram illustrating a terrestrial wireless communications system according to the prior art.

FIG. 2 is a schematic diagram illustrating a satellite wireless communications system according to the prior art.

FIG. 3 is a schematic diagram illustrating a technique for generating spread spectrum signals according to the prior art.

FIG. 4 is a schematic diagram illustrating exemplary components of a wireless communications system according to an embodiment of the present invention.

FIG. 5 is a schematic diagram illustrating an interference-compensating transmitter according to an embodiment of the present invention.

FIG. 6 is a schematic diagram illustrating an interference-compensating transmitter according to another embodiment of the present invention.

FIG. 7 is a schematic diagram illustrating an interference-compensating circuit according to another embodiment of the present invention.

FIGS. 8-10 are flowcharts illustrating exemplary interference compensation operations according to embodiments of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

The present invention now will be described more fully hereinafter with reference to the accompanying drawings, in which preferred embodiments of the invention are shown. This invention may, however, be embodied in many different forms and should not be construed as limited to the embodiments set forth herein; rather, these embodiments are provided so that this disclosure will be thorough and complete, and will fully convey the scope of the invention to those skilled in the art. In the drawings, like numbers refer to like elements. Although embodiments of the present invention described herein relate to spread spectrum code division multiple access (CDMA) wireless communications systems, in particular, to proposed IS-2000 (cdma2000) systems, it will be appreciated by those skilled in the art that the present invention is applicable to other wireless communications systems. It will also be appreciated that the present invention may also be used in other communications applications, including wireline and optical communications applications.

FIG. 4 illustrates components of a wireless communications system **400** according to an embodiment of the present invention. The wireless communications system includes a base station **420** and a mobile switching center (MSC) **410** that is operatively associated with the base station **420**. It will be appreciated the base station **420** may comprise any of a number of different types of apparatus that perform base station functions but are referred to using different nomenclature, including, but not limited to, base transceiver stations (BTS), "cell sites", "radio heads" and the like.

The base station **420** includes a controller **422** that communicates with the MSC **410**, and that may provide a number of different monitoring and/or control functions at the base station **420**. The base station **420** also includes an interference-compensating transmitter **424** that is operatively associated with the controller and that transmits coded signals in a wireless communications medium via an antenna **426**. The coded signals transmitted by the interference-compensating transmitter **424** may represent information received from the MSC **410**, such as speech or other data for transmission to a terminal (e.g., a cellular telephone). The interference-compensating transmitter **424** may generate the coded signals using various techniques as described below.

A baseband model of a signal generated by a conventional transmission technique, such as that illustrated in FIG. 3, as received at a receiver, may be given by:

$$r(t) = \sum_{i=1}^{K_1} d_i^1(t) Q_i^1(t) + \sum_{j=1}^{K_2} d_j^2(t) Q_j^2(t), \quad (4)$$

where d_i^s represents a complex symbol to be transmitted using the i th code in a s th group of a quasi-orthogonal code set, and the symbol duration is $T=NT_c$. In equation (4), multiplication with the pilot channel, fading and noise are ignored for purposes of illustration. The output of the receiver for the n th code of the second group is given by:

$$Z_n^2 = \int_0^T r(t) \tilde{Q}_n^2(t) dt = d_n^2 T + \sum_{i=1}^{K_1} d_i^1 C_i^1. \quad (5)$$

The second term in the right hand side of equation (5) represents interference affecting the n th channel in the second group.

According to an aspect of the present invention, this interference term may be compensated for at the transmitter to reduce the interference in the signal received at the receiver. A first case will now be described in which it is desired to compensate for interference arising from codes of a first group of a quasi-orthogonal code set on a channel using the n th code in a second group of codes of the quasi-orthogonal code set.

FIG. 5 illustrates an interference-compensating transmitter **500** according to this aspect of the present invention. A composite signal generating circuit **510** generates a composite signal $\sum_{m=1}^{K_1} d_m^1 Q_m^1$ from a set of K_1 first information symbols $d_1^1(t), d_2^1(t), \dots, d_{K_1}^1(t)$. Each of the first information symbols $d_1^1(t), d_2^1(t), \dots, d_{K_1}^1(t)$ is modulated by respective spreading codes $Q_1^1(t), Q_2^1(t), \dots, Q_{K_1}^1(t)$ from a first group of orthogonal spreading codes of a set of quasi-orthogonal spreading code using multiplier circuits **512**. The resulting signals are then combined by a summing circuit **514** to produce the composite signal $\sum_{m=1}^{K_1} d_m^1 Q_m^1$.

The composite signal $\sum_{m=1}^{K_1} d_m^1 Q$ is applied to an interference-compensating coded signal generating circuit **520**. The interference-compensating coded signal generator circuit **520** includes a multiplier circuit **521** that multiplies the composite signal $\sum_{m=1}^{K_1} d_m^1 Q$ by a complex conjugate of the n th spreading code $Q_n^2(t)$ of the second group produced by a complex conjugating circuit **522**. A scaling integrating circuit **523** integrates the resulting signal over a symbol interval T , normalized by the symbol duration T and scaled by a scaling factor α_2 . The scaled and integrated product $V_n^1(t)$ of the composite signal $\sum_{m=1}^{K_1} d_m^1 Q$ and the spreading code $Q_n^2(t)$ is then subtracted from an information symbol $d_n^2(t)$ in a subtraction circuit **524** to produce an interference-compensated information symbol $\hat{d}_n^2(t)$, which is then multiplied by the spreading code $Q_n^2(t)$ in a multiplier circuit **525** to produce a coded signal $r_n^2(t)$. The coded signal $r_n^2(t)$ is then combined with the composite signal $\sum_{m=1}^{K_1} d_m^1 Q$ in a summing circuit **530** to produce a combined signal $r(t)$ for transmission in the wireless communications medium.

The scaled and integrated product $V_n^1(t)$ may be given by:

$$\begin{aligned} V_n^1 &= \frac{\alpha_2}{T} \int_0^T \left[\sum_{m=1}^{K_1} d_m^1(t) Q_m^1(t) \right] \tilde{Q}_n^2(t) dt \\ &= \frac{\alpha_2}{T} \sum_{m=1}^{K_1} d_m^1 C_{m,n}^{1,2} \end{aligned} \quad (6)$$

where α_2 is a positive constant ≤ 1 . Over the symbol duration T , $V_n^1(t)$ is constant.

Accordingly, the transmitted combined signal $r(t)$ may be given by:

$$r(t) = \sum_{i=1}^{K_1} d_i^1(t) Q_i^1(t) + \sum_{j=1}^{K_2} [d_j^2(t) - V_j^1] Q_j^2(t) \quad (7)$$

The first term in the right hand side of equation (7) is the composite signal

$\sum_{m=1}^{K_1} d_m^1 Q$, while the second term in the right hand side of equation (7) represents the

interference-compensated signal for the signal generated according to the n th code

from the second group. The output of a receiver attempting to receive the signal

5 encoded according to the n th code (assuming no fading or other interference) may be given by:

$$\begin{aligned} Z_n^2 &= \int_0^T r(t) \tilde{Q}_n^2(t) dt = d_n^2 - V_n^1 T + \sum_{i=1}^{K_1} d_i^1 C_i^1, \\ &= d_n^2 T + (1 - \alpha_2) \sum_{i=1}^{K_1} d_i^1 C_{i,n}^{1,2}. \end{aligned} \quad (8)$$

10 In equation (8), the term $d_n^2 T$ represents the desired signal, while the term

$(1 - \alpha_2) \sum_{i=1}^{K_1} d_i^1 C_{i,n}^{1,2}$ represents interference arising from the codes of the first group.

Comparing equation (8) with equation (5), the interference from the codes from the first group is canceled to an extent determined by the scaling factor α_2 , for example,

if $\alpha_2 = 1$ the interference theoretically is completely canceled. From equation (8)

15 (ignoring channel Gaussian noise and fading), the received signal to interference ratio (SIR) for the channel encoded according to the n th code from the second group may be given by:

$$SIR_2 = \frac{N^2}{K_1 x^2 (1 - \alpha_2)}. \quad (9)$$

20

Looking at the interference on channels encoded according to codes from the first group, the output of a receiver receiving a channel encoded according to the n th code $Q_n^1(t)$ from the first group may be given by:

25

$$Z_n^1 = \int_0^T r(t) \tilde{Q}_n^1(t) dt = d_n^1 T + \sum_{j=1}^{K_2} d_j^2 - V_j^1 C_j^2. \quad (10)$$

Equation (10) may be manipulated to yield:

$$Z_n^1 = d_n^1 T_c \left(N - \alpha_2 K_2 x^2 / N \right) + \sum_{j=1}^{K_2} d_j^2 C_{j,n}^{2,1} - \frac{\alpha_2}{T} \sum_{j=1}^{K_2} C_{j,n}^{2,1} \sum_{\substack{m=1 \\ m \neq n}}^{K_1} d_m^1 C_m^1. \quad (11)$$

- 5 The first term on the right hand side of equation (11) corresponds to the desired signal, while the second term is similar to the interference term in equation (7) and represents interference that would arise from signal encoded according to codes in the second group if these signals were not compensated. The third term in equation (11) is an additional interference term arising from the use of compensation in signals transmitted according to codes from the second group.

The value of α_2 preferably is selected to produce desired signal to interference characteristics for the signals. The SIR of a channel encoded according to a code from the first group may be estimated by:

$$15 \quad SIR_1 = \frac{N - \alpha_2 K_2 x^2 / N^2}{x^2 K_2 + x^4 \alpha_2^2 K_2 / K_1 - 1}. \quad (12)$$

- One criteria for selecting the scaling factor α is to equalize estimated SIR for all active channels. Generally, the degree of improvement in estimated SIR over an uncompensated transmitter increases as the difference between the number K_1 of active channels using codes from the first set and the number K_2 of active channels using codes from the second group increases.

- 20 According to another aspect of the present invention, mutual interference in signals generated from both groups of codes can be compensated. FIG. 6 illustrates an interference-compensating transmitter **600** according to this aspect of the present invention. The interference-compensating transmitter **600** includes a first composite signal generating circuit **510a** that generates a first composite signal $\sum_{m=1}^{K_1} d_m^1 Q_m^1$ from first information symbols $d_1^1(t), d_2^1(t), \dots, d_{K_1}^1(t)$ and corresponding spreading codes $Q_1^1(t), Q_2^1(t), \dots, Q_{K_1}^1(t)$ from a first orthogonal group of the quasi-orthogonal code set. A second composite signal generating circuit **510b** generates a second composite

signal $\sum_{m=1}^{K_2} d_m^2 Q$ from second information symbols $d_1^2(t), d_2^2(t), \dots, d_{K_2}^2(t)$ and

corresponding spreading codes $Q_1^2(t), Q_2^2(t), \dots, Q_{K_2}^2(t)$ from a second orthogonal group of the quasi-orthogonal code set. Each of the first and second composite signal generating circuits **510a**, **510b** includes multiplier circuits **512** and a summing circuit

5 **514**, which function as described with reference to FIG. 5.

The first and second composite signals $\sum_{m=1}^{K_1} d_m^1 Q$, $\sum_{m=1}^{K_2} d_m^2 Q$ produced by the

first and second composite signal generating circuits **510a**, **510b** are applied to respective first and second sets of interference-compensating coded signal generating circuits **520a-1**, **520a-K2**, **520b-1**, **520b-K1** to produce interference-

10 compensated coded signals $r_1^1(t), \dots, r_{K_1}^1(t), r_1^2(t), \dots, r_{K_2}^2(t)$ that are combined by a summing circuit **610** to produce a combined signal $r(t)$ for transmission in the wireless communications medium. Each of the first and second interference-compensating coded signal generating circuits **520a-1**, **520a-K2**, and **520b-1**, **520b-K1** include multiplier circuits **521**, **525** and summing circuits **524** that function
15 as described with reference to FIG. 5. The first interference-compensating coded signal generating circuits **520a-1**, **520a-K1** that produce coded signals $r_1^1(t), \dots, r_{K_1}^1(t)$ from the codes for the first group of codes each include a scaling integrating circuit **523a** that employs a first scaling factor α_1 . The second interference-compensating coded signal generating circuits **520b-1**, **520b-K2**
20 that produce coded signals $r_1^2(t), \dots, r_{K_2}^2(t)$ from the codes for the second group of codes each include a scaling integrating circuit **523b** that employs a second scaling factor α_2 .

The combined signal $r(t)$ in this case is given by:

25
$$r(t) = \sum_{i=1}^{K_1} [d_i^1(t) - V_i^2] Q_i^1(t) + \sum_{j=1}^{K_2} [d_j^2(t) - V_j^1] Q_j^2(t) \quad (13)$$

Respective SIRs SIR_1, SIR_2 for channels coded according to the respective first and second groups of codes may be given by:

$$SIR_1 = \frac{N - \alpha_2 K_2 x^2 / N^2}{1 - \alpha_1^2 x^2 K_2 + x^4 \alpha_2^2 K_2 K_1 - 1} \quad (14)$$

and

$$SIR_2 = \frac{N - \alpha_1 K_1 x^2 / N^2}{1 - \alpha_2^2 x^2 K_1 + x^4 \alpha_1^2 K_1 K_2 - 1} \quad (15)$$

- 5 When α_1 and α_2 are chosen to equalize estimated SIR among the signals, improvement in SIR generally increases as the difference between K_1 and K_2 increases.

- The present invention is also applicable when more than two groups of codes are used. An exemplary interference-compensating coded signal generating circuit
- 10 **520'** for a channel encoded according to a j th code $Q_j^1(t)$ of a first group of codes using such an application is illustrated in FIG. 7. Composite signals
- $$\sum_{m=1}^{K_2} d_m^2 Q_m^2, \sum_{m=1}^{K_3} d_m^3 Q_m^3, \sum_{m=1}^{K_4} d_m^4 Q_m^4$$
- for respective second, third and fourth groups of codes are each multiplied by the complex conjugate of the j th code $Q_j^1(t)$, and then integrated over a symbol period T and scaled by a scaling factor α_j by respective
- 15 scaling integrating circuits **532a'**, **532b'**, **523c'**. The scaled and integrated signals produced are then subtracted from the information symbol $d_j^1(t)$ at a subtraction circuit **524'** to produce an interference-compensated information symbol $\hat{d}_j^1(t)$. The interference-compensated information symbol $\hat{d}_j^1(t)$ is then multiplied by the j th code $Q_j^1(t)$ to produce a coded signal $r_j^1(t)$, which can be combined with other coded
- 20 signals and transmitted as described with reference to FIGs. 5-7.

- FIGs. 8-10 are flowcharts illustrating exemplary operations for decoding variably encoded signals according to aspects of the present invention. It will be understood that blocks of the flowcharts of FIGs. 8-10, and combinations of blocks in the flowchart illustrations, may be implemented using electronic circuits included in a
- 25 transmitting station, such as the transmitter components illustrated in FIGs. 4-7. It will also be appreciated that blocks of the flowchart illustrations of FIGs. 8-10, and combinations of blocks in the flowchart illustrations, may be implemented using

components other than those illustrated in FIGs. 4-7, and that, in general, the blocks of the flowchart illustrations of FIGs. 8-10, and combinations of blocks in the flowcharts, may be implemented in special purpose hardware such as discrete analog and/or digital circuitry, combinations of integrated circuits or one or more application specific integrated circuits (ASICs), as well as by computer program instructions which may be loaded onto a computer or other programmable data processing apparatus to produce a machine such that the instructions which execute on the computer or other programmable data processing apparatus implement the functions specified in the flowchart block or blocks. The computer program instructions may also be loaded onto a computer or other programmable data processing apparatus to cause a series of operational steps to be performed on the computer or other programmable apparatus to produce a computer implemented process such that the instructions which execute on the computer or other programmable apparatus provide steps for implementing the functions specified in the flowchart block or blocks.

Accordingly, blocks of the flowchart illustrations of FIGs. 8-10 support electronic circuits and other means for performing the specified functions, as well as combinations of steps for performing the specified functions. It will be understood that the circuits and other means supported by each block of the flowcharts of FIGs. 8-10, and combinations of blocks therein, can be implemented by special purpose hardware, software or firmware operating on special or general purpose data processors, or combinations thereof.

FIG. 8 illustrates exemplary interference-compensated signal transmission operations **800** according to an embodiment of the present invention. An interference-compensated information symbol is generated from an information symbol based on knowledge of an information symbol and a first code used to produce a first coded signal (Block **810**). A second coded signal representing the interference-compensated information symbol encoded according to a second code is transmitted concurrently with transmission of the first coded signal (Block **820**). It will be appreciated that the operations **800** can be implemented in a number of different ways, including the ways described with reference to FIGs. 5-7.

In exemplary operations **900** according to an embodiment of the present invention illustrated in FIG. 9, a set of quasi-orthogonal codes including first and second orthogonal groups is identified (Block **910**). At least one information symbol is encoded according to at least one code from the first group to generate a composite

signal (Block 920). A product of the composite signal and the complex conjugate of one of the codes of the second group is integrated over a symbol period (Block 930), and the resulting integrated product scaled according to a scaling factor (Block 940). The scaled integrated product is then subtracted from a source information symbol to generate an interference-compensated information symbol (Block 950). The interference-compensated information symbol is then encoded (e.g., multiplied) according to the code from the second group to generate a coded signal (Block 960). The coded signal is then combined with other coded signals, e.g., other coded signals generated in a similar fashion or the composite signal itself, to generate a combined signal (Block 970) that is transmitted in the communications medium (Block 980).

FIG. 10 illustrates exemplary operations 1000 according to yet another aspect of the present invention. Respective numbers K_1 , K_2 of channelization codes actively in use from first and second groups of a quasi-orthogonal code set are identified (Block 1010). One or more values for one or more scaling factors α are determined such that estimated SIRs for the channels coded according to the active codes are equalized based on the numbers K_1 , K_2 using, for example, the relations given in equations (14) and (15) (Block 1020). The selected values are then applied to generate one or more interference-compensated coded signals (Block 1030). The one or more interference-compensated coded signals are then transmitted (Block 1040).

It will be appreciated by those skilled in the art that the operations illustrated in FIGs. 5-10 may be varied within the scope of the present invention. For example, it may be desirable to select scaling factors to provide estimated SIR for some channels (e.g., channels that are more vulnerable to transmission errors) that is greater than that applied in other channels, instead of equalizing SIR among all channels. Criteria other than SIR may also be used to determine appropriate scaling factors. In other variations, instead of determining scaling factors for each symbol period, a transmitter may simply toggle between interference-compensated and non-interference-compensated modes of operation based on a threshold evaluation of the relative number of codes from different groups that are actively in use.

In the drawings and specification, there have been disclosed typical preferred embodiments of the invention and, although specific terms are employed, they are used in a generic and descriptive sense only and not for purposes of limitation, the scope of the invention being set forth in the following claims.

CLAIMS

THAT WHICH IS CLAIMED IS:

1. A method of transmitting comprising:
generating an interference-compensated information symbol from a source information symbol based on knowledge of an information symbol and a first code used to generate a first coded signal; and
5 concurrently transmitting the first coded signal and a second coded signal representing the interference-compensated information symbol encoded according to a second code.
2. The method according to Claim 1:
wherein generating an interference-compensated information symbol from a source information symbol based on knowledge of an information symbol and a first code used to generate a first coded signal is preceded by generating a first composite
5 signal from at least one information symbol according to at least one code from a first group of codes of a set of quasi-orthogonal codes;
wherein generating an interference-compensated information symbol from a source information symbol based on knowledge of an information symbol and a first code used to generate a first coded signal comprises generating a first interference-
10 compensated information symbol from a first information symbol, the first composite signal and a code from a second group of codes of the set of quasi-orthogonal codes;
and
wherein the second coded signal represents the first interference-compensated information symbol encoded according to the code from the second group of codes.
3. The method according to Claim 2, wherein generating a first interference-compensated information symbol from a first information symbol, the first composite signal and a code from a second group of codes of the set of quasi-orthogonal codes comprises:
5 integrating a product of the first composite signal and the complex conjugate of the code from the second group of codes over a symbol interval;
scaling the integrated product by a scaling factor; and

subtracting the scaled integrated product from the first information symbol to generate the first interference-compensated information symbol.

10

4. The method according to Claim 3, wherein scaling the integrated product by a scaling factor is preceded by:

determining respective first and second numbers of codes from the first group of codes and codes from the second group of codes to be used to transmit information symbols for the symbol interval; and

5

determining the scaling factor based on the determined first and second numbers.

5. The method according to Claim 4, wherein determining the scaling factor based on the determined first and second numbers comprises determining the scaling factor from the determined first and second numbers using a signal quality criterion.

5

6. The method according to Claim 5, wherein determining the scaling factor from the determined first and second numbers using a signal quality criterion comprises selecting the scaling factor such that it produces substantially equal estimated signal to interference ratios for signals coded according to the first and second codes.

5

7. The method according to Claim 2:

wherein the first coded signal is the first composite signal;

wherein concurrently transmitting the first coded signal and a second coded signal representing the interference-compensated information symbol encoded according to a second code is preceded by :

5

encoding the first interference-compensated symbol according to the code from the second group of codes to produce the second coded signal; and combining the first composite signal and the second coded signal to produce a combined signal; and

10

wherein concurrently transmitting the first coded signal and a second coded signal representing the interference-compensated information symbol encoded according to a second code comprises transmitting the combined signal.

8. The method according to Claim 2:

wherein concurrently transmitting the first coded signal and a second coded signal representing the interference-compensated information symbol encoded according to a second code is preceded by :

- 5 identifying at least one information symbol to be transmitted
using at least one code from the second group of codes;
generating a second composite signal from the at least one
information symbol to be transmitted using the at least one code from
the second group of codes according to the at least one code from the
10 second group of codes; and
generating a second interference-compensated information
symbol from a second information symbol, the second composite
signal and a code from the first group of codes; and
wherein the first coded signal represents the second interference-compensated
15 information symbol encoded according to the code from the first group of codes.

9. The method according to Claim 8:

wherein concurrently transmitting the first coded signal and a second coded signal representing the interference-compensated information symbol encoded according to a second code is preceded by :

- 5 encoding the second interference-compensated information symbol
according to the code from the first group of codes to produce the first coded
signal; and
combining the first and second coded signals to produce a combined
signal; and
10 wherein concurrently transmitting the first coded signal and a second coded
signal representing the interference-compensated information symbol encoded
according to a second code comprises transmitting the combined signal.

10. The method according to Claim 8, wherein generating a second interference-compensated information symbol from a second information symbol comprises :

- integrating a product of the second composite signal and the complex
5 conjugate of the code from the first group of codes over a symbol interval;
scaling the integrated product by a scaling factor; and
subtracting the scaled integrated product from the second information symbol
to generate the second interference-compensated information symbol.

11. The method according to Claim 10, wherein scaling the integrated
product by a scaling factor is preceded by :
determining respective first and second numbers of codes from the first group
of codes and codes from the second group of codes to be used to transmit information
5 symbols for the symbol interval; and
determining the scaling factor based on the determined first and second
numbers.

12. The method according to Claim 11, wherein determining the scaling
factor based on the determined first and second numbers comprises determining the
scaling factor from the first and second numbers based on a signal quality criterion.

13. The method according to Claim 12, wherein determining the scaling
factor based on the determined first and second numbers comprises selecting the
scaling factor such that it produces substantially equal estimated signal to interference
ratios for signals modulated according to the first and second codes.

14. The method according to Claim 1, wherein concurrently transmitting
the first coded signal and a second coded signal representing the interference-
compensated information symbol encoded according to a second code comprises
concurrently transmitting the first coded signal and the second coded signal in a
5 wireless communications medium from at least one wireless base station.

15. The method according to Claim 2, wherein the codes of the first group
of codes are orthogonal to one another, and wherein the codes of the second group of
codes are orthogonal to one another.

16. The method according to Claim 2 wherein the set of quasi-orthogonal codes comprises a set of quasi-orthogonal spreading codes.

17. In a wireless communications system in which at least one base station is operative to transmit on respective channels defined by respective spreading codes selected from a set of quasi-orthogonal spreading codes, the set of quasi-orthogonal spreading codes including a first group of orthogonal spreading codes and a second group of orthogonal spreading codes, a method of transmitting comprising :
5 generating an interference-compensated information symbol from a source information symbol based on knowledge of an information symbol and a code from the first group of codes used to generate a first coded signal; and
concurrently transmitting the first coded signal and a second coded signal
10 representing the interference-compensated information symbol encoded according to a code from the second group of codes.

18. The method according to Claim 17, wherein generating an interference-compensated information symbol from a source information symbol based on knowledge of an information symbol and a code from the first group of codes used to generate a first coded signal comprises :
5 encoding at least one information symbol according to at least one code from the first group of codes to generate a composite signal;
integrating a product of the composite signal and the complex conjugate of the code from the second group of codes over a symbol interval;
scaling the integrated product by a scaling factor; and
10 subtracting the scaled integrated product from the source information symbol to generate the interference-compensated information symbol.

19. The method according to Claim 18, wherein scaling the integrated product by a scaling factor is preceded by :
determining a first number of codes from the first group of codes and second number of codes from the second group of codes to be used to transmit information
5 symbols for the symbol interval; and
determining the scaling factor based on the determined first and second numbers.

20. The method according to Claim 17, wherein concurrently transmitting the first coded signal and a second coded signal representing the interference-compensated information symbol encoded according to a code from the second group of codes comprises concurrently transmitting the first and second coded signals from
5 the same base station.

21. A communications system, comprising:
at least one transmitter that generates an interference-compensated information symbol from a source information symbol based on knowledge of an information symbol and a first code used to generate a first coded signal and that concurrently
5 transmits the first coded signal and a second coded signal representing the interference-compensated information symbol encoded according to a second code.

22. The system according to Claim 21, wherein said at least one transmitter comprises:
a composite signal generating circuit that generates a composite signal from at least one information symbol according to at least one code from a first group of
5 codes of a set of quasi-orthogonal codes; and
an interference-compensating coded signal generating circuit that generates the interference-compensated information symbol from the source information symbol, the composite signal and a code from a second group of codes of the set of quasi-orthogonal codes, and that generates the second coded signal from the
10 interference-compensated information symbol according to the code from the second group of codes.

23. The system according to Claim 22, wherein said interference-compensating coded signal generating circuit integrates a product of the composite signal and the complex conjugate of the code from the second group of codes over a symbol interval, scales the integrated product by a scaling factor, and subtracts the
5 scaled integrated product from the source information symbol to generate the interference-compensated information symbol.

24. The system according to Claim 23, wherein said interference-compensating coded signal generating circuit determines respective first and second numbers of codes from the first group of codes and codes from the second group of codes to be used to transmit information symbols for the symbol interval and
5 determines the scaling factor based on the determined first and second numbers.

25. The system according to Claim 21, wherein said at least one transmitter comprises at least one wireless transmitter positioned at a wireless base station.

26. The system according to Claim 25, wherein said at least one wireless base station comprises a single wireless base station that concurrently transmits the first and second coded signals.

27. The system according to Claim 22, wherein the codes of the first group of codes are orthogonal to one another, and wherein the codes of the second group of codes are orthogonal to one another.

28. The system according to Claim 22 wherein the set of quasi-orthogonal codes comprises a set of quasi-orthogonal spreading codes.

29. A transmitting station, comprising:
means for generating an interference-compensated information symbol from a source information symbol based on knowledge of an information symbol and a first code used to generate a first coded signal; and
5 means for concurrently transmitting the first coded signal and a second coded signal representing the interference-compensated information symbol encoded according to a second code.

30. The transmitting station according to Claim 29, further comprising:
means for generating a composite signal from at least one information symbol according to at least one code from a first group of codes of a set of quasi-orthogonal codes;

5 wherein said means for generating an interference-compensated information symbol from a source information symbol comprises means for generating an interference-compensated information symbol from the source information symbol, the composite signal and a code from a second group of codes of the set of quasi-orthogonal codes; and

10 wherein said means for concurrently transmitting comprises means for transmitting a second coded signal representing the first interference-compensated information symbol encoded according to the code from the second group of codes.

31. The transmitting station according to Claim 30, wherein said means for generating the interference-compensated information symbol comprises:

 means for integrating a product of the composite signal and the complex conjugate of the code from the second group of codes over a symbol interval;

5 means for scaling the integrated product by a scaling factor; and

 means for subtracting the scaled integrated product from the source information symbol to generate the interference-compensated information symbol.

32. The transmitting station according to Claim 31, further comprising:

 means for determining respective first and second numbers of codes from the first group of codes and codes from the second group of codes to be used to transmit information symbols from the transmitting station for the symbol interval; and

5 means for determining the scaling factor based on the determined first and second numbers.

33. A wireless communications base station, comprising:

 an interference-compensating transmitter operative to transmit on respective channels defined by respective spreading codes selected from a set of quasi-

 orthogonal spreading codes, the set of quasi-orthogonal spreading codes including a

5 first group of orthogonal spreading codes and a second group of orthogonal spreading codes, said transmitter further operative to generate an interference-compensated information symbol from a source information symbol based on knowledge of an information symbol and a code from the first group of codes used to generate a first coded signal and to concurrently transmit a second coded signal representing the

- 10 interference-compensated information symbol encoded according to a code from the second group of codes.

34. The base station according to Claim 33, wherein said transmitter comprises:

a composite signal generating circuit that encodes at least one first information symbol according to at least one code from the first group of codes to generate a

- 5 composite signal; and

an interference-compensating coded signal generating circuit that integrates a product of the composite signal and the complex conjugate of the code from the second group of codes over a symbol interval, scales the integrated product by a scaling factor, and subtracts the scaled integrated product from the source information

- 10 symbol to generate the interference-compensated information symbol.

35. The base station according to Claim 34, wherein said interference-compensating coded signal generating circuit determines a first number of codes from the first group of codes and a second number of codes from the second group of codes to be used to transmit information symbols from the base station for the symbol

5 interval and determines the scaling factor based on the determined first and second numbers.

36. The base station according to Claim 33, wherein said transmitter concurrently transmits the first and second coded signals.

ABSTRACT OF THE DISCLOSURE

In a communications system such as a wireless code division multiple access (CDMA) communications system, an interference-compensated information symbol is generated from a source information symbol based on knowledge of an information symbol and a first code used to generate a first coded signal. The first
5 coded signal and a second coded signal representing the interference-compensated information symbol encoded according to a second code are then concurrently transmitted. In one embodiment, a composite signal is generated from at least one information symbol according to at least one code from a first group of codes of a set of quasi-orthogonal codes. An interference-compensated information symbol is then
10 generated from a source information symbol, the composite signal and a code from a second group of codes of the set of quasi-orthogonal codes. The second coded signal represents the interference-compensated information symbol encoded according to the code from the second group, and is transmitted concurrently with transmission of the first coded signal. Preferably, the interference-compensated information symbol is
15 generated by integrating a product of the composite signal and the complex conjugate of the code from the second group over a symbol interval, scaling the integrated product by a scaling factor, and subtracting the scaled integrated product from the source information symbol to generate the interference-compensated information symbol.




Fig. 1
Prior Art




FIG. 3




FIG. 3
Prior Art




FIG. 4




FIG. 5



FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10

DECLARATION AND POWER OF ATTORNEY FOR PATENT APPLICATION

Attorney Docket No. 8194-368

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name.

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled **METHODS, SYSTEMS AND APPARATUS FOR PRECOMPENSATING FOR INTERFERENCE AMONG TRANSMITTED CODED SIGNALS**,

the specification of which

☒ [X] is attached hereto

OR

☐ [] was filed on _____ as United States Application No. or PCT International Application Number _____ and was amended on _____ (if applicable).

I hereby state that I have reviewed and understand the contents of the above-identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to patentability as defined in Title 37 Code of Federal Regulations, § 1.56.

I hereby claim foreign priority benefits under Title 35, United States Code, § 119(a)-(d) or § 365(b) of any foreign application(s) for patent or inventor's certificate, or § 365(a) of any PCT International application which designated at least one country other than the United States of America, listed below and have also identified below any foreign application for patent or inventor's certificate, or of any PCT International application having a filing date before that of the application on which priority is claimed.

None			<input type="checkbox"/> [] Yes <input type="checkbox"/> [] No
Number	Country	MM/DD/YYYY Filed	Priority Claimed

			<input type="checkbox"/> [] Yes <input type="checkbox"/> [] No
Number	Country	MM/DD/YYYY Filed	Priority Claimed

			<input type="checkbox"/> [] Yes <input type="checkbox"/> [] No
Number	Country	MM/DD/YYYY Filed	Priority Claimed

I hereby claim the benefit under Title 35, United States Code, § 119(e) of any United States provisional application(s) listed below.

None	
Application Number(s)	Filing Date (MM/DD/YYYY)

Application Number(s)	Filing Date (MM/DD/YYYY)

I hereby claim the benefit under Title 35, United States Code, § 120 of any United States application(s) or § 365(c) of any PCT international application designating the United States of America, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT International application(s) in the manner provided by the first paragraph of Title 35, United States Code, § 112, I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, § 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application (37 C.F.R. § 1.63(d)).

None		
Appln. Serial No.	Filing Date	Status Patented/Pending/Abandoned

Appln. Serial No.	Filing Date	Status Patented/Pending/Abandoned

Appln. Serial No.	Filing Date	Status Patented/Pending/Abandoned

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

POWER OF ATTORNEY: As a named inventor, I hereby appoint the practitioners associated with the Customer Number provided below to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith, and direct that all correspondence be addressed to that Customer Number:

Customer Number 20792

Send correspondence to: Robert M. Meeks
Myers Bigel Sibley & Sajovec, P.A.
Post Office Box 37428
Raleigh, North Carolina 27627

Direct telephone calls to: Robert M. Meeks
(919) 854-1400

Facsimile: (919) 854-1401

Full name of sole inventor: **Essam Sourour**

Inventor's
Signature: Essam Sourour Date: 3/2/2000

Residence: Cary , North Carolina

Citizenship: Egypt

Post Office Address: 1305 Seabrook Avenue
Cary, North Carolina 27511